




MB SEQ functions - quick reference

Detailed info for options and functions is available at
http://www.ucapps.de/midibox_seq_manual_m.html

#	Function	Description / Options
Dedicated button functions (these can vary depending on panel design and MBSEQ_HW.V4 file)		
1	Pattern 1,2,3,4	Select pattern/track group - G1, G2, G3, G4
2	Track 1,2,3,4	Select track within track group - T1, T2, T3, T4. 16 tracks are available in total
3	Trigger layer A,B,C	Select trigger layer A or B or C. Holding C opens trigger layer selection menu and allows to select others Gate Acc Roll Glide Skip R.G(random gate) R.V(random value) No FX
4	Parameter layer A,B,C	Select parameter layer A and B. C switches between C & D or with <i>Pressed&Hold</i> open parameter layer selection menu and allows to select others. Four parameter layers available by default, but CC, Pitch, Prob, Delay can be added via trigger selection menu (?) 
5	Step View	View and select steps if more than 16 are used 1..16 17..32 ...etc
6	Pattern	Select/load pattern/track group G1, G2, G3, G4 from SD memory location
7	Song	Select song parameters Song # Position Action{Stop; x1..x16; Jump Pos; Jump Song; Mixer; Tempo; Mutes} Select patterns: G1,G2,G3,G4
8	Edit	Enter edit mode to edit parameter layer step values and set trigger layer steps
9	Mute	Quickly mute/unmute tracks 1...16
10	Solo	Solo current track
11	←/→ (Left/Right)	Move cursor position. <i>Left</i> has limited usage
12	+/- (Inc/Dec)	Same as <i>Jog Dial</i> encoder - increases/decreases the current value
13	Exit	Quickly exit to top menu
14	Select	(<i>Press&Hold</i>) Select steps to be controlled by <i>All</i> function. Obviously has usage in other situations as well 

#	Function	Description / Options
15	All	Edit all selected steps set with <i>Select</i> function
16	Copy	Copy steps from selected # to #. Selection can be edited by <i>Select</i> function
17	Paste	Paste copied steps starting from # step. Selection can be edited by <i>Select</i> function
18	F1 (Clear)	(Press&Hold) Wipe selected track. Other functions can be assigned in MBSEQ_HW.V4 file
19	F2 (Select track)	(Press&Hold) Select track. Other functions can be assigned in MBSEQ_HW.V4 file
20	F3 (Select parameter layer)	(Press&Hold) Select parameter layer A,B,C,D...etc. Other functions can be assigned in MBSEQ_HW.V4 file
21	F4 (Select trigger layer)	(Press&Hold) Select/assign trigger layer 1..8. Other functions can be assigned in MBSEQ_HW.V4 file
22	Rec	Open record menu Track # Record{Live; Step} Mode{Mono; Poly} AStart{on; off} Step # TglGate Port # Chn #
23	«	Rewind. Active only in song mode
24	Stop	Stop playback and reset position to beginning
25	Play	Start playback of patterns/song
26	Pause	Halt/resume playback
27	»	Forward. Active only in song mode
28	Metronome	Toggle metronome on/off
29	Fast	Activate <i>Fast</i> mode for quicker value selection with encoders. Speed options for <i>Fast</i> can be changed in MBSEQ_HW.V4 file
30	Scrub	(Press&Hold) + Jog Wheel dynamically change actual position
Menu functions		
31	Menu+Scrub	Toggle loop mode on/off
32	Menu+GP1 (Mixer)	Open mixer view for 16 tracks. 12 pages can be switched with +/- . An additional options available with <i>Select</i> button  Fix Me! Midi port Midi channel Prog change Volume Panorama Reverb Chorus CC1 CC2 CC3 CC4
33	Menu+GP2 (Event)	Open track setup editor Track # Type{Note; Chord; CC; Drum} Step # ParL # TrgL # Port # Chn # Edit Name

#	Function	Description / Options
34	Menu+GP3 (Mode)	Open track mode editor Track # Track on/off Normal, Transpose, Arpeggiator Hold{on; off} Sort{on; off} Restart{on; off} Scale{on; off} Sustain{on; off}
35	Menu+GP4 (Direction)	Open track playback direction editor Track # Select playback mode: Forward, Backward, PingPong, Pendulum, Rand.Dir, Rand.Step, Rand.D+S Fwd # Back # Replay # Repeat # Skip # Itv # SyncM{yes; no}
36	Menu+GP5 (Divider)	Open track clock divider setup editor Track # Clock # Divider{normal; triplet} Sync to Measure{on; off} Timebase selector: 1, 2, 4, 8 ..etc
37	Menu+GP6 (Length)	Open track length editor Track # Length # Loop # Quick length selection: 4, 8, 16 ..etc
38	Menu+GP7 (Transpose)	Open track transpose editor Track # Transpose selector: -7 oct ... +7 oct -7 sem ... +7 sem

4

a

b

From:

<http://www.midibox.org/dokuwiki/> - **MIDIbox**

Permanent link:

http://www.midibox.org/dokuwiki/doku.php?id=midibox_seq_quick_reference&rev=1273342551

Last update:

2010/05/08 19:15