MIDIBox AY 3 8912 - PATCH MENU

Access the **PATCH MENU** via **F1**

The Patch Menu:

LCD ROW	Func.	Data	Memo
1	NAME:	PATCH NAME	Edit the Patch Name here
2	NR :	0 to 127	Select the Patch here (Patch 0 = PIC internal Patch / 1 to 127 = Bankstick Patches)
3	DO :	L W F	Do **L**oad Patch, **W**rite Patch, **F**ormat Bankstick1
4	status	(info)	(**W**: OK, **L**: OK, **F**: BS PATCH 1-127)

Annotation:

LCD ROW	EDIT	KEYS
1	NAME	Use A-Z, 0-9, SPACE = "_", after Patch Name Editing the user can delete the Patch Name via INST DEL key
2	Nr.	Use crsr ← → (+ / -)
3	Do	Use L W F
4	status	(info)

- Bankstick = Bankstick1 by default
- A " **!** " before the [Patch Name] (@LCD ROW1) indicates, that the Patch is NOT loaded yet.
- The Fx Data is included (will be stored)
- Patchname Cursor Pos. +1 = [CRSR →] or [+] or [>]
- Patchname Cursor Pos. -1 = [CRSR ←|(+SHIFT)] or [-] or [<]
- [INS DEL] or [CLR HOME] delete the patch name after patch name editing (this do not delete the patch data).

From:
https://www.midibox.org/dokuwiki/ - **MIDIbox**

Permanent link:
https://www.midibox.org/dokuwiki/doku.php?id=midibox_ay_patch_menu&rev=1258883800

Last update: **2009/11/22 09:56**