MB SEQ functions - quick reference

Detailed info for options and functions is available at
http://www.ucapps.de/midibox_seq_manual_m.html

#	Function	Description / Options									
Dedicated button functions *(theese can vary depending on panel design and MBSEQ_HW.V4 file)*											
1	Pattern 1,2,3,4	Select pattern/track group - G1, G2, G3, G4									
2	Track 1,2,3,4	Select track within track group - T1, T2, T3, T4 (16 tracks are available in total)									
3	Trigger layer A,B,C	Select trigger layer A or B or C. Holding C opens trigger layer selection menu and allows to select others <html>	Gate	Acc	Roll	Glide	Skip	R.G(random gate)	R.V(random value)	No FX	</html>
4	Parameter layer A,B,C	Select parameter layer A and B. C switches between C & D or if *Pressed&Hold* opens parameter layer selection menu and allows to select others. Four parameter layers available by default, but CC, Pitch, Prob, Delay can be added via trigger selection menu *(?)* Fix Me! <html>	Note	Vel	Length	Roll	</html>				
5	Step View	View and select steps if more than 16 are used <html>	1..16	17..32	...etc</html>						
6	Pattern	Select/load pattern/track group G1, G2, G3, G4 from SD memory location									
7	Song	Select song parameters <html>	Song #	Position	Action{Stop; x1..x16; Jump Pos; Jump Song; Mixer; Tempo; Mutes}		Select patterns G1,G2,G3,G4	</html>			

#	Function	Description / Options									
8	Edit	Enter edit mode to edit parameter layer step values and set trigger layer steps									
9	Mute	Quickly mute/unmute tracks 1...16									
10	Solo	Solo current track									
11	←/→ *(Left/Right)*	Move cursor position (Left has limited usage)									
12	+/- *(Inc/Dec)*	Same as *Jog Dial* encoder - increases/decreases the current value									
13	Exit	Quickly exit to top menu									
14	Select	*(Press&Hold)* Select steps to be controlled by *All* function *(obviously has usage in other situations as well)* Fix Me!									
15	All	Edit all selected steps set with *Select* function									
16	Copy	Copy steps from selected # to # (Selection can be edited by *Select* function)									
17	Paste	Paste copied steps starting from # step (Selection can be edited by *Select* function)									
18	F1 *(Clear)*	*(Press&Hold)* Wipes selected track (Other functions can be assigned in MBSEQ_HW.V4 file)									
19	F2 *(Select track)*	*(Press&Hold)* Selects track (Other functions can be assigned in MBSEQ_HW.V4 file)									

#	Function	Description / Options									
20	F3 *(Select parameter layer)*	*(Press&Hold)* Selects parameter layer (Other functions can be assigned in MBSEQ_HW.V4 file)									

4 a b

From:
https://www.midibox.org/dokuwiki/ - **MIDIbox**

Permanent link:
https://www.midibox.org/dokuwiki/doku.php?id=midibox_seq_quick_reference&rev=1273338752

Last update: **2010/05/08 17:12**