



MB SEQ functions - quick reference

Detailed info for options and functions is available at http://www.ucapps.de/midibox_seq_manual_m.html

#	Function	Description / Options											
Dedicated button functions <i>(these can vary depending on panel design and MBSEQ_HW.V4 file)</i>													
1	Pattern 1,2,3,4	Select pattern/track group - G1, G2, G3, G4											
2	Track 1,2,3,4	Select track within track group - T1, T2, T3, T4. 16 tracks are available in total											
3	Trigger layer A,B,C	Select trigger layer A or B or C. Holding C opens trigger layer selection menu and allows to select others <html>	Gate	Acc	Roll	Glide	Skip	R.G(random gate)	R.V(random value)	No FX	</html>		
4	Parameter layer A,B,C	Select parameter layer A and B. C switches between C & D or with <i>Pressed&Hold</i> open parameter layer selection menu and allows to select others. Four parameter layers available by default, but CC, Pitch, Prob, Delay can be added via trigger selection menu (?)  Fix Me! <html>	Note	Vel	Length	Roll	</html>						
5	Step View	View and select steps if more than 16 are used <html>	1..16	17..32	...etc</html>								
6	Pattern	Select/load pattern/track group G1, G2, G3, G4 from SD memory location											
7	Song	Select song parameters <html>	Song #	Position	Action{Stop; x1..x16; Jump Pos; Jump Song; Mixer; Tempo; Mutes}	Select patterns G1,G2,G3,G4	</html>						
8	Edit	Enter edit mode to edit parameter layer step values and set trigger layer steps											
9	Mute	Quickly mute/unmute tracks 1...16											
10	Solo	Solo current track											
11	←/→ (Left/Right)	Move cursor position. Left has limited usage											

#	Function	Description / Options											
12	+/- (Inc/Dec)	Same as <i>Jog Dial</i> encoder - increases/decreases the current value											
13	Exit	Quickly exit to top menu											
14	Select	(<i>Press&Hold</i>) Select steps to be controlled by <i>All</i> function. Obviously has usage in other situations as well 											
15	All	Edit all selected steps set with <i>Select</i> function											
16	Copy	Copy steps from selected # to #. Selection can be edited by <i>Select</i> function											
17	Paste	Paste copied steps starting from # step. Selection can be edited by <i>Select</i> function											
18	F1 (<i>Clear</i>)	(<i>Press&Hold</i>) Wipe selected track. Other functions can be assigned in MBSEQ_HW.V4 file											
19	F2 (<i>Select track</i>)	(<i>Press&Hold</i>) Select track. Other functions can be assigned in MBSEQ_HW.V4 file											
20	F3 (<i>Select parameter layer</i>)	(<i>Press&Hold</i>) Select parameter layer A,B,C,D...etc. Other functions can be assigned in MBSEQ_HW.V4 file											
21	F4 (<i>Select trigger layer</i>)	(<i>Press&Hold</i>) Select/assigns trigger layer 1..8. Other functions can be assigned in MBSEQ_HW.V4 file											
22	Rec	Open record menu <html>	Track #	Record{Live; Step}	Mode{Mono; Poly}	AStart{on; off}	Step #	TglGate		Port #	Chn #	</html>	
23	«	Rewind. Active only in song mode											
24	Stop	Stop playback and reset position to beginning											
25	Play	Start playback of patterns/song											
26	Pause	Halt/resume playback											

#	Function	Description / Options										
27	»	Forward. Active only in song mode										
28	Metronome	Toggle metronome on/off										
29	Fast	Activate <i>Fast</i> mode for quicker value selection with encoders. Speed options for <i>Fast</i> can be changed in MBSEQ_HW.V4 file										
30	Scrub	<i>(Press&Hold) + Jog Wheel</i> dynamically change actual position										
4	a	b										

From:

<https://www.midibox.org/dokuwiki/> - **MIDIbox**

Permanent link:

https://www.midibox.org/dokuwiki/doku.php?id=midibox_seq_quick_reference&rev=1273340762Last update: **2010/05/08 17:46**