

MB SEQ functions - quick reference

Detailed info for options and functions is available at http://www.ucapps.de/midibox_seq_manual_m.html

#	Function	Description / Options													
Dedicated button functions (these can vary depending on panel design and MBSEQ_HW.V4 file)															
1	Pattern 1,2,3,4	Select pattern/track group - G1, G2, G3, G4													
2	Track 1,2,3,4	Select track within track group - T1, T2, T3, T4. 16 tracks are available in total													
3	Trigger layer A,B,C	Select trigger layer A or B or C. Holding C opens trigger layer selection menu and allows to select others <html>	Gate	Acc	Roll	Glide	Skip	R.G(random gate)	R.V(random value)	No FX	</html>				
4	Parameter layer A,B,C	Select parameter layer A and B. C switches between C & D or with <i>Press&Hold</i> open parameter layer selection menu and to select others. Four parameter layers available by default, but CC, Pitch, Prob, Delay can be added via trigger selection menu (?) 	Note	Vel	Length	Roll	</html>								
5	Step View	View and select steps if more than 16 are used <html>	1..16	17..32	...etc</html>										
6	Pattern	Select/load pattern/track group G1, G2, G3, G4 from SD memory location													
7	Song	Select song parameters <html>	Song #	Position	Action{Stop; x1..x16; Jump Pos; Jump Song; Mixer; Tempo; Mutes}	Select patterns: G1,G2,G3,G4	</html>								
8	Edit	Enter edit mode to edit parameter layer step values and set trigger layer steps													
9	Mute	Quickly mute/unmute tracks 1...16													
10	Solo	Solo current track													
11	←/→ (Left/Right)	Move cursor position. Left has limited usage													
12	+/- (Inc/Dec)	Same as Jog Dial encoder - increases/decreases the current value													
13	Exit	Quickly exit to top menu													

#	Function	Description / Options																		
14	Select	<i>(Press&Hold)</i> Select steps to be controlled by <i>All</i> function. <u>Obviously has usage in other situations as well (which?)</u> 																		
15	All	Edit all selected steps set with <i>Select</i> function																		
16	Copy	Copy steps from selected # to #. Step # can be edited by <i>Select</i> function																		
17	Paste	Paste copied steps starting from # step. Step # can be edited by <i>Select</i> function																		
18	F1 <i>(Clear)</i>	<i>(Press&Hold)</i> Wipe selected track. Other functions can be assigned in MBSEQ_HW.V4 file																		
19	F2 <i>(Select track)</i>	<i>(Press&Hold)</i> Select track. Other functions can be assigned in MBSEQ_HW.V4 file																		
20	F3 <i>(Select parameter layer)</i>	<i>(Press&Hold)</i> Select parameter layer A,B,C,D...etc. Other functions can be assigned in MBSEQ_HW.V4 file																		
21	F4 <i>(Select trigger layer)</i>	<i>(Press&Hold)</i> Select/assign trigger layer 1..8. Other functions can be assigned in MBSEQ_HW.V4 file																		
22	Rec	Open record menu <html>	Track #	Record{Live; Step}	Mode{Mono; Poly}	AStart{on; off}	Step #	TglGate		Port #	Chn #	</html>								
23	«	Rewind. Active only in song mode																		
24	Stop	Stop playback and reset position to beginning																		
25	Play	Start playback of patterns/song																		
26	Pause	Halt/resume playback																		
27	»	Forward. Active only in song mode																		
28	Metronome	Toggle metronome on/off																		
29	Fast	Activate <i>Fast</i> mode for quicker value selection with encoders. Speed options for <i>Fast</i> can be changed in MBSEQ_HW.V4 file																		
30	Scrub	<i>(Press&Hold)</i> + <i>Jog Wheel</i> dynamically change actual position																		
Menu functions																				

Last update:

2010/05/09 midibox_seq_quick_reference https://www.midibox.org/dokuwiki/doku.php?id=midibox_seq_quick_reference&rev=1273423001
16:36

From:

<https://www.midibox.org/dokuwiki/> - **MIDIbox**

Permanent link:

https://www.midibox.org/dokuwiki/doku.php?id=midibox_seq_quick_reference&rev=1273423001

Last update: **2010/05/09 16:36**

