# MIDIBox AY 3 8912 - PATCH MENU

Access the **PATCH MENU** via **F1**

### The Patch Menu:

| LCD ROW | Func. | Data | Memo |
|---|---|---|---|
| 1 | NAME: | PATCH NAME | Edit the Patch Name here |
| 2 | NR : | 0 to 127 | Patch 0 = PIC internal Patch / 1 to 127 = Bankstick Patches |
| 3 | DO : | L W F | **L**oad Patch, **W**rite Patch, **F**ormat Bankstick1 |
| 4 | status | (info) | |

### Annotation:

| LCD ROW | EDIT | KEYS |
|---|---|---|
| 1 | NAME | Use A-Z, 0-9, SPACE = "_", after Patch Name Editing the user can delete the Patch Name via INST DEL key |
| 2 | Nr. | Use crsr ← → (+ / -) |
| 3 | Do | Use L W F |
| 4 | status | (info) |

- Bankstick = Bankstick1 by default
- A " **!** " before the [Patch Name] (@LCD ROW1) indicates, that the Patch is NOT loaded yet.
- The Fx Data is included (will be stored)

From:
https://www.midibox.org/dokuwiki/ - **MIDIbox**

Permanent link:
**https://www.midibox.org/dokuwiki/doku.php?id=midibox_ay_patch_menu&rev=1258883341**

Last update: **2009/11/22 09:49**