

SCP and MSA #defines for the SpeakJet



ImportantNote:

This file is currently under development and can change radically!

Maybe you want to wait some days until this note disappears to add your SJ-Definitions

It can be used for your C-based MBHP_IIC_SpeakJet Project:

Feel free to edit and add defines!

```
/*
 * IIC_SpeakJetDefines.h
 * kII.2
 *
 * Created by Michael Markert, audiocommander.de on 20.05.06
 * Based on Speakjet control codes from July 27, 2004 version of Speakjet
Manual
 * and ASM-Version of Doug Elliott, VA3DAE
 *
 * Released under CreativeCommons 2.5 by-nc-sa
 * http://creativecommons.org/licenses/by-nc-sa/2.5/
 */

#ifndef _IIC_SPEAKJETDEFINES_H
#define _IIC_SPEAKJETDEFINES_H

// ***** SPEAKJET MIDI ASSIGNMENTS * //
#ifdef _DEBUG_C
    #pragma mark -
    #pragma mark SPEAKJET MIDI ASSIGNMENTS
#endif

// MIDI ASSIGNMENTS
// optimized for KORG microKONTROL

#define SJCC_PHRASE                20
// pads 1 - 8: call phrase
#define SJCC_PHRASE0                21
#define SJCC_PHRASE1                22
#define SJCC_PHRASE2                23
#define SJCC_PHRASE3                24
#define SJCC_PHRASE4                25
#define SJCC_PHRASE5                26
```

```
#define SJCC_PHRASE6          27
#define SJCC_PHRASE7          28
// pads 9 - 12: slow/low/high/fast
#define SJCC_NEXT_SLOW        29
#define SJCC_NEXT_LOW         30
#define SJCC_NEXT_HIGH        31
#define SJCC_NEXT_FAST        32
// pads 13 - 16: pause 0(0ms) / 1(100ms) / 2(200ms) / 3(700ms)
#define SJCC_PAUSE0           33
#define SJCC_PAUSE1           34
#define SJCC_PAUSE2           35
#define SJCC_PAUSE3           36

// Encoders 1 - 5: OSCx Level
#define SJCC_OSC1_LVL         101
#define SJCC_OSC2_LVL         102
#define SJCC_OSC3_LVL         103
#define SJCC_OSC4_LVL         104
#define SJCC_OSC5_LVL         105
// Sliders 1 - 5: OSCx Frequency
#define SJCC_OSC1_FREQ        111
#define SJCC_OSC2_FREQ        112
#define SJCC_OSC3_FREQ        113
#define SJCC_OSC4_FREQ        114
#define SJCC_OSC5_FREQ        115

// Encoder 6 - 8: ENV CTR / DIST / SPEED
#define SJCC_ENV_TYPE          106
#define SJCC_DISTORTION        107
#define SJCC_SPEED             108
// Slider 6 - 8: ENV FREQ / NEXT LOUD / MASTER VOL
#define SJCC_ENV_FREQ          116
#define SJCC_NEXT_LOUD         117
#define SJCC_MASTER_VOL        118

// Joystick X: Pitch
// Joystick Y: Bend

// not used, but implemented:
#define SJCC_PITCH             255
#define SJCC_BEND              255

// ***** SPEAKJET SCP ***** //
```

```
// Serial Control Protocol
#ifdef _DEBUG_C
    #pragma mark -
    #pragma mark SCP
#endif

// escape character ('\') 0x5C to enter SCP Mode
#define SCP_ESCAPE                '\\\
#define SCP_SEL0                  '0'
#define SCP_SEL1                  '1'
#define SCP_SEL2                  '2'
#define SCP_SEL3                  '3'
#define SCP_SEL4                  '4'
#define SCP_SEL5                  '5'
#define SCP_SEL6                  '6'
#define SCP_SEL7                  '7'
#define SCP_EXIT                  'X'

#define SCP_READY                 'V'
#define SCP_CLEAR_BUFFER         'R'
#define SCP_START                 'T'
#define SCP_STOP                 'S'

#define SCP_MEMTYPE              'H'
#define SCP_MEMADDR              'J'
#define SCP_MEMWRT               'N'

#define SCP_RESET                'W'

// ***** SPEAKJET SCP REGISTERS ***** //
// SCP Registers & MAX Values
#ifdef _DEBUG_C
    #pragma mark -
    #pragma mark SCP REGISTERS & MAX VALUES
#endif

// == SCP_MEMTYPE (H) ==
#define SCP_MEMTYPE_REGISTER     '0'
#define SCP_MEMTYPE_EEPROM_H    '3'
#define SCP_MEMTYPE_EEPROM_L    '2'

// == SCP_MEMADDR (J) ==
// Envelope
#define SCP_ENV_FREQ             '0'
#define SCP_ENV_CTRL            '8'
/* Oscillator Frequency Register
#define SCP_OSC1_FREQ           '1'
#define SCP_OSC2_FREQ           '2'
#define SCP_OSC3_FREQ           '3'
#define SCP_OSC4_FREQ           '4'
```

```
#define SCP_OSC5_FREQ          '5' */
/* Oscillator Level Register (send each digit as ASCII!)
#define SCP_OSC1_LEVEL          11
#define SCP_OSC2_LEVEL          12
#define SCP_OSC3_LEVEL          13
#define SCP_OSC4_LEVEL          14
#define SCP_OSC5_LEVEL          15*/
// Distortion
#define SCP_DISTORTION          '6'
// Master
#define SCP_MASTER_VOLUME      '7'

// == SCP_MEMWRT (N) ==
//   ENVType (send ENVType + ENVState!)
#define SCP_ENV_SAW             0x0
#define SCP_ENV_SINE            0x1
#define SCP_ENV_TRIANGLE        0x2
#define SCP_ENV_SQUARE          0x3
//   ENVState (send ENVType + ENVState!)
#define SCP_ENV_OSC123          0x40
#define SCP_ENV_OSC45           0x80
// Maximum accepted values
#define SCP_FREQ_MAX            3999
#define SCP_LEVEL_MAX           31 // 63 MAX for Mixer 1
#define SCP_DISTORTION_MAX      255
#define SCP_MASTER_VOLUME_MAX  255

// ***** SPEAKJET MSA ***** //
// Mathematical Sound Architecture
#ifdef _DEBUG_C
    #pragma mark -
    #pragma mark MSA Control Codes
#endif

// 0 - 31 CONTROL CODES
#define MSA_PAUSE0              0
#define MSA_PAUSE1              1
#define MSA_PAUSE2              2
#define MSA_PAUSE3              3
#define MSA_PAUSE4              4
#define MSA_PAUSE5              5
```

```
#define MSA_PAUSE6          6

#define MSA_NEXTFAST       7
#define MSA_NEXTSLOW      8
#define MSA_NEXTHIGH      14
#define MSA_NEXTLOW       15

#define MSA_WAIT           16

#define MSA_VOLUME         20
#define MSA_SPEED          21
#define MSA_PITCH          22
#define MSA_BEND           23

#define MSA_PORTCTR        24
#define MSA_PORT           25

#define MSA_REPEAT         26

#define MSA_CALLPHRASE     28
#define MSA_GOTOPHRASE     29

#define MSA_DELAY          30
#define MSA_RESET          31

// 32 - 127 (Reserved)
#ifdef _DEBUG_C
    #pragma mark MSA (Reserved)
#endif

// 128 - 254 SOUND_CODES
#ifdef _DEBUG_C
    #pragma mark MSA Sound Codes
#endif

// MSA Sound Codes: Phonemes
#define MSAPH_IY           128
#define MSAPH_IH           129
#define MSAPH_EY           130
#define MSAPH_EH           131
#define MSAPH_AY           132
#define MSAPH_AX           133
#define MSAPH_UX           134
#define MSAPH_OH           135
#define MSAPH_AW           136
#define MSAPH_OW           137
#define MSAPH_UH           138
#define MSAPH_UW           139
#define MSAPH_MM           140
#define MSAPH_NE           141
#define MSAPH_NO           142
```

```
#define MSAPH_NGE          143
#define MSAPH_NGO          144
#define MSAPH_LE           145
#define MSAPH_LO           146
#define MSAPH_WW           147
#define MSAPH_RR           148
#define MSAPH_IYRR         149
#define MSAPH_EYRR         150
#define MSAPH_AXRR         151
#define MSAPH_AWRR         152
#define MSAPH_OWRR         153
#define MSAPH_EYIY         154
#define MSAPH_OHIY         155
#define MSAPH_OWIY         156
#define MSAPH_OHIH         157
#define MSAPH_IYEH         158
#define MSAPH_EHLL         159
#define MSAPH_IYUW         160
#define MSAPH_AXUW         161
#define MSAPH_IHWW         162
#define MSAPH_AYWW         163
#define MSAPH_OWWW         164
#define MSAPH_JH           165
#define MSAPH_VV           166
#define MSAPH_ZZ           167
#define MSAPH_ZH           168
#define MSAPH_DH           169
#define MSAPH_BE           170
#define MSAPH_BO           171
#define MSAPH_EB           172
#define MSAPH_OB           173
#define MSAPH_DE           174
#define MSAPH_DO           175
#define MSAPH_ED           176
#define MSAPH_OD           177
#define MSAPH_GE           178
#define MSAPH_GO           179
#define MSAPH_EG           180
#define MSAPH_OG           181
#define MSAPH_CH           182
#define MSAPH_HE           183
#define MSAPH_HO           184
#define MSAPH_WH           185
#define MSAPH_FF           186
#define MSAPH_SE           187
#define MSAPH_SO           188
#define MSAPH_SH           189
#define MSAPH_TH           190
#define MSAPH_TT           191
#define MSAPH_TU           192
```

```
#define MSAPH_TS          193
#define MSAPH_KE          194
#define MSAPH_KO          195
#define MSAPH_EK          196
#define MSAPH_OK          197
#define MSAPH_PE          198
#define MSAPH_PO          199

// MSA Sound Codes: Robot
#define MSAFX_ROBOT_0     200
#define MSAFX_ROBOT_1     201
#define MSAFX_ROBOT_2     202
#define MSAFX_ROBOT_3     203
#define MSAFX_ROBOT_4     204
#define MSAFX_ROBOT_5     205
#define MSAFX_ROBOT_6     206
#define MSAFX_ROBOT_7     207
#define MSAFX_ROBOT_8     208
#define MSAFX_ROBOT_9     209

// MSA Sound Codes: Alarms
#define MSAFX_ALARM_0     210
#define MSAFX_ALARM_1     211
#define MSAFX_ALARM_2     212
#define MSAFX_ALARM_3     213
#define MSAFX_ALARM_4     214
#define MSAFX_ALARM_5     215
#define MSAFX_ALARM_6     216
#define MSAFX_ALARM_7     217
#define MSAFX_ALARM_8     218
#define MSAFX_ALARM_9     219

// MSA Sound Codes: Beeps
#define MSAFX_BEEP_0      220
#define MSAFX_BEEP_1      221
#define MSAFX_BEEP_2      222
#define MSAFX_BEEP_3      223
#define MSAFX_BEEP_4      224
#define MSAFX_BEEP_5      225
#define MSAFX_BEEP_6      226
#define MSAFX_BEEP_7      227
#define MSAFX_BEEP_8      228
#define MSAFX_BEEP_9      229

// MSA Sound Codes: Biological
#define MSAFX_BIO_0       230
#define MSAFX_BIO_1       231
#define MSAFX_BIO_2       232
#define MSAFX_BIO_3       233
#define MSAFX_BIO_4       234
#define MSAFX_BIO_5       235
```

```
#define MSAFX_BIO_6          236
#define MSAFX_BIO_7          237
#define MSAFX_BIO_8          238
#define MSAFX_BIO_9          239

// MSA Sound Codes: DTMF
#define MSAFX_DTMF_0         240
#define MSAFX_DTMF_1         241
#define MSAFX_DTMF_2         242
#define MSAFX_DTMF_3         243
#define MSAFX_DTMF_4         244
#define MSAFX_DTMF_5         245
#define MSAFX_DTMF_6         246
#define MSAFX_DTMF_7         247
#define MSAFX_DTMF_8         248
#define MSAFX_DTMF_9         249
#define MSAFX_DTMF_S         250
#define MSAFX_DTMF_R         251

// MSA Sound Codes: Misc
#define MSAFX_SONAR_PING     252
#define MSAFX_PISTOLSHOT     253
#define MSAFX_WOW            254

// 255: End of Phrase
#ifdef _DEBUG_C
    #pragma mark MSA EOP
#endif

#define MSA_EOP              255

#endif /* _IIC_SPEAKJETDEFINES_H */
```

From:
<https://www.midibox.org/dokuwiki/> - **MIDibox**

Permanent link:
https://www.midibox.org/dokuwiki/doku.php?id=speakjet_definition_list&rev=1150246509

Last update: **2006/10/15 09:35**

